

How to Restore the IP-100 to Factory Settings

Restoring the IP-100 to factory settings is always advisable when experiencing trouble with your Internet connection or other signal issues, or if you suspect mistakes were made during changes to the internal page of the IP-100. Restoring the IP-100 to factory settings is always a good place to start. Please read through all directions before you begin.

Please note that the 'reset' button will be held down during this ENTIRE procedure.

1. Press and hold the reset button.
2. Disconnect power to the IP-100 for 10 seconds.
3. Reconnect power to the IP-100.
4. Continue to hold the reset button until the front three lights turn off (Radio Data, Ethernet, Status).
5. Once the lights go off, release the reset button.

* DO NOT unplug the IP-100 for the next 10 minutes. It takes up to 10 minutes for the IP-100 to talk to the server, reload its information and connect again. **Unplugging the IP-100 during an update or original boot-up will disable the IP-100 and it will have to be sent back to RainWise to be corrected.**

The factory restore has now been completed.